



12v AC
Door Release
With Monitor switch

At	Terminal	Function
D/U	D	Speech from door
D/U	E	Speech to door
PSU	12	12v AC for ringing & lock
PSU	0	12v AC for ringing & lock
PSU	+	12v DC for speech & lamps
PSU	-	12v DC for speech & lamps
TEL	A2	Ringer Warble
TEL	A1	Ringer buzzer (if fitted)
TEL	L	Speech from door
TEL	P	Speech to door
TEL	1	Lock button
TEL	B	Common for ringers
TEL	F	Common for speech
TEL	G	Common for buttons
TEL	COM	Switch common
TEL	UP	Switch in UP position
TEL	DWN	Switch in DOWN position
TEL	LED-	RED LED negative
TEL	DOI	GREEN LED Door Open negative

Plan 1	Provides Ringing, Communication and Door Release functions.
201 Phones	These have additional features, with 206S PCB fitted.
206S	An ON/OFF (CHOS) switch with Red LED, and DOI Door Open Indicator Green LED with normally open door sensor is fitted.
Notes	Insert LINKS everywhere shown. Ringer Warble volume, all phones have a spindle at the top left corner. Speech volume is adjustable on the back of the entrance panel. Speaker and Microphone have separate controls.

Title :	WDA_1-3_201+206S	
Date :	Nov 2023	Drawn by : TH
Application :	Plan 1 – Multi Button D/U – 201 and 206S	